

# *SOM-iMX6M*

## User Manual

---

*October 2015*

*Revision 1.00*

*Copyright © 2015*

*EMAC, Inc.*

**Table of Contents**

1 Introduction..... - 4 -

    1.1 .... *Features*..... - 4 -

2 Hardware..... - 5 -

    2.1 .... *Specifications* ..... - 5 -

    2.2 .... *Real-Time Clock*..... - 6 -

    2.3 .... *Watchdog Timer*..... - 7 -

    2.4 .... *External Connections*..... - 7 -

        2.4.1 JTAG ..... - 7 -

        2.4.2 System Control..... - 7 -

        2.4.3 One-Wire / I2C ..... - 8 -

        2.4.4 Ethernet..... - 9 -

        2.4.5 USB ..... - 10 -

        2.4.6 HSIC..... - 12 -

        2.4.7 SPI ..... - 13 -

        2.4.8 MCI Multimedia Card ..... - 14 -

        2.4.9 Serial Ports..... - 15 -

        2.4.10 I2S..... - 16 -

        2.4.11 CAN ..... - 17 -

        2.4.12 GPIO..... - 17 -

        2.4.13 LVDS..... - 19 -

        2.4.14 HDMI ..... - 20 -

        2.4.15 CSI..... - 21 -

        2.4.16 DSI ..... - 21 -

        2.4.17 PCIe..... - 22 -

        2.4.18 SATA ..... - 23 -

        2.4.19 Battery Control ..... - 23 -

        2.4.20 Analog to Digital Converter ..... - 24 -

        2.4.21 Touch Screen Interface ..... - 24 -

    2.5 .... *Power Connections*..... - 25 -

    2.6 .... *Boot Options*..... - 26 -

    2.7 .... *Serial Data Flash*..... - 26 -

2.8	.... <i>Module Status LED</i> .....	- 26 -
3	Design Considerations.....	- 26 -
3.1	.... <i>Power</i> .....	- 27 -
3.1.1	Shutdown Logic Pins .....	<b>Error! Bookmark not defined.</b>
3.1.2	Battery Backup.....	- 27 -
3.1.3	Analog Reference.....	- 27 -
3.1.4	Analog Voltage.....	<b>Error! Bookmark not defined.</b>
4	Software .....	- 27 -

## Disclaimer

EMAC Inc. does not assume any liability arising out of the application or use of any of its products or designs. Products designed or distributed by EMAC Inc. are not intended for, or authorized to be used in, applications such as life support systems or for any other use in which the failure of the product could potentially result in personal injury, death or property damage.

If EMAC Inc. products are used in any of the aforementioned unintended or unauthorized applications, Purchaser shall indemnify and hold EMAC Inc. and its employees and officers harmless against all claims, costs, damages, expenses, and attorney fees that may directly or indirectly arise out of any claim of personal injury, death or property damage associated with such unintended or unauthorized use, even if it is alleged that EMAC Inc. was negligent in the design or manufacture of the product.

EMAC Inc. reserves the right to make changes to any products with the intent to improve overall quality, without further notification.



## 1 Introduction

This document describes EMAC's SoM-iMX6M System on Module (SoM). The SoM-iMX6M is a System on Module, designed to be compatible with EMAC's 314-pin SODIMM form factor. This module is built around the Freescale i.MX6 microcontroller, which provides several of its key features.

The SoM-iMX6M comes with either a single, dual, or quad core processor to suit a wide variety of needs. The SoM has Gigabit Ethernet, PCIe, and SATA interfaces. There are two SDIO/MMC ports, two SPI ports and two I2S ports. There are four RS232 serial ports available, three with RTS/CTS handshaking and one with full handshaking. Any of these four ports can be configured for RS485 hardware flow control. There are two high speed USB 2.0 host ports and one high speed USB 2.0 OTG port. The SoM has support for three different video interfaces that include HDMI, 24-bit LVDS and DSI. The SoM-iMX6M also has a CSI interface for video capture. There are two CAN interfaces and two I2C interfaces along with a battery charge control interface. The SoM has 22 GPIO pins, four of which support PWM and two are for a general purpose timer.

In addition to the standard SoM features, the SoM-iMX6M also features open source software support and a wide range of controller I/O pins.

### 1.1 Features

- **Freescale i.MX6 Microcontroller**
- **Multiple Video Output Including HDMI, LVDS and DSI**
- **Video Input Support Through CSI**
- **Gigabit Ethernet**
- **High Speed USB 2.0**
- **SATA II**
- **PCIe**
- **SDIO/MMC**
- **I2S/AC97 Audio**
- **I2C**
- **SPI**
- **CAN**
- **RS232 Serial Ports**
- **Various GPIO**

## **2 Hardware**

### **2.1 Specifications**

#### **Microcontroller**

- **CPU: Single/Dual/Quad ARM™ Cortex™ -A9 MPcore with Cortex-A9 NEON MPE**

#### **Memory**

- **Flash: 16MB Serial NOR Flash**
- **RAM: Up to 2GB DDR3 @ 800MHz**
- **eMMC: Up to 4GB of Onboard eMMC**

#### **Video**

- **LVDS: 1 24bit, 165 Mpixels/sec, LVDS Interface**
- **HDMI: 1 HDMI 1.4 Port**
- **MIPI/DSI: 2 Lanes @ 1Gbps**
- **MIPI/CSI: 4 Lanes @ 1Gbps Each**

#### **Serial Interfaces**

- **UARTS: 4 Serial Ports, 3 with RTS/CTS Handshaking and 1 with Full Handshaking**
- **SPI: 2 Serial Peripheral Interfaces with 3 Chip Selects Each**
- **USB: 2 USB 2.0 High Speed Host Ports and 1 USB 2.0 High Speed OTG Port**
- **PCI: 1 Lane PCIe (Gen 2.0)**
- **I2C: 2 General Use 400Kbps I2C Ports and Dedicated I2C Ports for LVDS and HDMI Interfaces**
- **I2S: 2 I2S/AC97 Audio Interfaces up to 1.4Mbps Each**

#### **Ethernet Interface**

- **MAC: i.MX6 MAC Utilizing RGMII Interface**
- **PHY: Micrel KSZ9031 Gigabit Ethernet PHY**
- **Interface: Media Dependant Interface (MDI)**

#### **Miscellaneous**

- **SDIO/MMC: 2 4bit SDIO/MMC Interfaces Supporting SDHC Cards up to 32GB**

- **Reset:** MAX6747 Watchdog Timer and Reset Supervisor
- **RTC:** MAX6747 Watchdog Timer and Reset Supervisor
- **Timer/Counters:** 1 General Purpose Timer Counter with Dedicated Clock Input
- **PWM:** 4 Channels of PWM Output
- **Watchdog Timer:** MAX6747 Watchdog Timer and Reset Supervisor
- **Digital I/O:** 22 General Purpose Input/Output lines
- **Analog I/O:** 4 Channel 12 bit Analog to Digital Converter
- **Power:** Single 5.0V Supply
- **JTAG:** Processor JTAG Supporting Programming, Trace and Boundary Scan
- **Clocks:** 24MHz Main Oscillator and a 32.768KHz RTC Oscillator

### Mechanical and Environmental

- **Dimensions:** 82.0 x 60.0 mm
- **Power Supply Voltage:** 5.0 VDC
- **Power Requirements (typical):**
  - 5.0 Volts @ ##00mA (XXX watts)
  - Max current draw during boot process: TBD
  - Constant busy loop: TBD
  - Idle system: TBD
  - Idle system with Ethernet PHY disabled: TBD
  - APM sleep mode with Ethernet PHY disabled: TBD
  - APM sleep mode with Ethernet PHY enabled: TBD
- **Operating Temperature:** -40 ~ 85° C (-40 ~ 185 ° F), fanless operation. 0 ~ 70° C (32 ~ 158° F)
- **Operating Humidity:** 0% ~ 90% relative humidity, non-condensing

## 2.2 Real-Time Clock


The SoM-iMX6M provides a real time clock through the use of the i.MX6 on-chip Secure Real Time Clock. The RTC is powered from a Lithium Ion battery supplied on the carrier. There is a dedicated 32.768KHz oscillator on the SoM-iMX6M to drive the processors RTC.

### 2.3 Watchdog Timer

A Watchdog timer is provided on the SoM-iMX6M by use of a MAX6747 Watchdog Timer and Reset Supervisor. The WDT is set for a timeout of approximately 1.4 seconds. The WDT can be disabled by writing GPIO1\_IO25 low. The WDT is pulsed by using processor pin GPIO1\_IO22.

### 2.4 External Connections

All external connections to the SoM-iMX6M are provided through a 314 pin card edge connector. The SoM utilizes an MM70-314 or equivalent connector on a carrier board to provide access to the various processor interfaces.



#### 2.4.1 JTAG

The SoM-iMX6M provides access to the i.MX6's JTAG interface for programming and debugging. Supports IEEE P149.1 and 1149.6.

#### Processor JTAG

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
46	JTAG_MOD	JTAG_MOD	JTAG Operation Mode
50	JTAG_TCK	JTAG_TCK	JTAG Clock
52	JTAG_TDI	JTAG_TDI	JTAG Serial In
56	JTAG_TDO	JTAG_TDO	JTAG Serial Out
58	JTAG_TMS	JTAG_TMS	
62	JTAG_TRST	JTAG_TRST	Test Reset Signal

#### 2.4.2 System Control

There are nine pins provided for system control. These include power and reset as well as boot mode selection (see i.MX6 datasheet for details on boot modes). The RST\_IN# and RST\_OUT# are buffered through the MAX6747 reset supervisor IC. There is a write protect line that connects directly to the serial NOR flash. This line is active low and is pulled up on the SoM through a 10K Ohm resistor. The VCC\_RTC pin is for connecting a battery for the real time clock and requires a 3.7V lithium battery.



## System Control

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
252	ON/OFF	ONOFF	N/A	On/Off Power button
253	S5	N/C	N/C	Power State S5
251	S3	N/C	N/C	Power State S3
74	BOOT_0	BOOT_MODE0	N/A	Boot Mode Selection 0
76	BOOT_1	BOOT_MODE1	N/A	Boot Mode Selection 1
254	RST_IN#	POR_B	N/A	Reset In (active low)
182	RST_OUT#	POR_B	N/A	Reset Out (active low)
281	VCC_RTC	LICELL (MMPF0100 Pin)	N/A	Real Time Clock Battery Backup
279	SF_WP#	WP# (N25Q128A Pin)	N/A	Serial Flash Write Protect (active low)

### 2.4.3 One-Wire / I2C

The SoM-iMX6M provides two I2C serial ports. Both are capable of 400kbps communication speeds. The I2C data and clock lines are pulled up to 3.3V through 4.7K resistors on the SoM so that none are required on the carrier.

#### I2C A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
231	I2C_A_SCL	I2C1_SCL	GPIO5_IO27	Two Wire Serial Interface Clock
233	I2C_A_SDA	I2C1_SDA	GPIO5_IO26	Two Wire Serial Interface Data

#### I2C B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
-------------	--------------	-----------------------	-----------	-------------

<b>235</b>	I2C_B_SCL	I2C2_SCL	GPIO2_IO30	Two Wire Serial Interface Clock
<b>237</b>	I2C_B_SDA	I2C2_SDA	GPIO3_IO16	Two Wire Serial Interface Data

#### 2.4.4 Ethernet

The SoM-iMX6M provides for 10/100/1000 BaseT Ethernet. The SoM is equipped with a Micrel KSZ9031 physical layer that is routed out to the card edge. A 1:1 Gigabit Ethernet transformer is required on the carrier board between the SoM and an RJ45 jack. The KSZ9031 provides on chip termination for the four Ethernet differential pairs so none are required on the carrier. An active low Ethernet Link and Activity LED signal is provided by the KSZ9031 and routed to the card edge. While EMAC's EM4C SoM Specification provides for dual Gigabit Ethernet the SoM-iMX6M only provides one.

#### Ethernet A

SODIMM Pin#	SoM Pin Name	KSZ9031 Pin Name	Description
<b>E4_3</b>	GBE_A_MDI0-	TXRXA_P	Gigabit Ethernet Media Dependant Interface Pair A0-
<b>E4_2</b>	GBE_A_MDI0+	TXRXA_N	Gigabit Ethernet Media Dependant Interface Pair A0+
<b>E4_6</b>	GBE_A_MDI1-	TXRXB_P	Gigabit Ethernet Media Dependant Interface Pair A1-
<b>E4_5</b>	GBE_A_MDI1+	TXRXB_N	Gigabit Ethernet Media Dependant Interface Pair A1+
<b>E3_3</b>	GBE_A_MDI2-	TXRXC_P	Gigabit Ethernet Media Dependant Interface Pair A2-
<b>E3_2</b>	GBE_A_MDI2+	TXRXC_N	Gigabit Ethernet Media Dependant Interface Pair A2+
<b>E3_6</b>	GBE_A_MDI3-	TXRXD_P	Gigabit Ethernet Media Dependant Interface Pair A3-
<b>E3_5</b>	GBE_A_MDI3+	TXRXD_N	Gigabit Ethernet Media Dependant Interface Pair A3+
<b>E3_7</b>	LED0_A_ACT	LED1/ PHYAD0	Ethernet Activity LED A, Active Low
<b>E4_9</b>	LED1_A_nLink1000	N/C	Ethernet Link1000 Status A, Active Low
<b>E4_8</b>	LED1_A_nLink100	LED2 /PHYAD1	Ethernet Link100 Status A, Active Low

#### Ethernet B

SODIMM Pin#	SoM Pin Name	{PHY} Pin Name	Description
108	GBE_B_MDI0-	N/C	Gigabit Ethernet Media Dependant Interface Pair B0-
106	GBE_B_MDI0+	N/C	Gigabit Ethernet Media Dependant Interface Pair B0+
112	GBE_B_MDI1-	N/C	Gigabit Ethernet Media Dependant Interface Pair B1-
110	GBE_B_MDI1+	N/C	Gigabit Ethernet Media Dependant Interface Pair B1+
118	GBE_B_MDI2-	N/C	Gigabit Ethernet Media Dependant Interface Pair B2-
116	GBE_B_MDI2+	N/C	Gigabit Ethernet Media Dependant Interface Pair B2+
122	GBE_B_MDI3-	N/C	Gigabit Ethernet Media Dependant Interface Pair B3-
120	GBE_B_MDI3+	N/C	Gigabit Ethernet Media Dependant Interface Pair B3+
134	LED0_B_ACT	N/C	Ethernet Activity LED B, Active Low
136	LED1_B_nLink1000	N/C	Ethernet Link1000 Status B, Active Low
138	LED1_B_nLink100	N/C	Ethernet Link100 Status B, Active Low

#### 2.4.5 USB

The SoM-iMX6M has three USB 2.0 ports. The EM4C specification provides for two USB 3.0 ports however the i.MX6 processor only supports USB 2.0 through the 3.0 interface. All USB Super Speed lines are no connect. There is a high speed USB 2.0 host/device port that supports OTG functionality. The USB OTG port is connected directly to the processor while the two host ports are achieved through the use of Microchip's USB2512 two port USB 2.0 hub controller. There are signals provided for USB OTG functionality as well as port power and over-current control for each USB port.

#### USB 2.0 Host

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
70	USB_C_D+	N/C	N/C	USB 2.0 Host C Data+
72	USB_C_D-	N/C	N/C	USB 2.0 Host C Data-

#### USB 2.0 Host/Device

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
64	USB_D_OTG_D+	USB_OTG_DP	N/A	USB 2.0 Host/Device D Data+
68	USB_D_OTG_D-	USB_OTG_DN	N/A	USB 2.0 Host/Device D Data-
84	OTG_PWR_EN	GPIO1	GPIO1_IO01	USB D On The Go Power Enable
161	USB_OTG_VBUS	USB_OTG_VBUS	N/A	USB D On The Go Voltage Bus Detect
155	USB_OTG_ID	USB_OTG_ID	GPIO1_IO24	USB D On The Go Device ID

### USB 3.0 A

SODIMM Pin#	SoM Pin Name	USB Pin Name(s)	Port Line	Description
167	USB_A_SS_RX+	N/C	N/C	USB A Super Speed RX Data+
169	USB_A_SS_RX-	N/C	N/C	USB A Super Speed RX Data-
173	USB_A_SS_TX+	N/C	N/C	USB A Super Speed TX Data+
175	USB_A_SS_TX-	N/C	N/C	USB A Super Speed TX Data-
181	USB_A_D+	USBDP_DN1 (USB2512 Pin)	N/A	USB A Host 2.0/3.0 Data+
179	USB_A_D-	USBDM_DN1 (USB2512 Pin)	N/A	USB A Host 2.0/3.0 Data-

### USB 3.0 B

SODIMM Pin#	SoM Pin Name	USB Pin Name(s)	Port Line	Description
143	USB_B_SS_RX+	N/C	N/C	USB B Super Speed RX Data+
145	USB_B_SS_RX-	N/C	N/C	USB B Super Speed RX Data-
149	USB_B_SS_TX+	N/C	N/C	USB B Super Speed TX Data+
151	USB_B_SS_TX-	N/C	N/C	USB B Super Speed TX Data-

157	USB_B_D+	USBDP_DN2 (USB2512 Pin)	N/A	USB B Host 2.0/3.0 Data+
159	USB_B_D-	USBDM_DN2 (USB2512 Pin)	N/A	USB B Host 2.0/3.0 Data-

### USB 3.0 Control

SODIMM Pin#	SoM Pin Name	USB Pin Name(s)	Port Line	Description
163	USB_PWR_EN	P RTPWR1/P RTPWR2 (USB2512 Pin)	N/A	USB 3.0 Voltage Bus Enable
183	USB_VBUS	USB_H1_VBUS (i.MX6 Pin)	N/A	USB 3.0 Voltage Bus Detect
139	USB_HUB_RST	RESET_N (USB2512 Pin)	N/A	Reset For external USB Hub
165	USB_OC_A	OCS_N1 (USB2512 Pin)	N/A	USB A Over Current Detect
141	USB_OC_B	OCS_N2 (USB2512 Pin)	N/A	USB B Over Current Detect

#### 2.4.6 HSIC

The EM4C SoM Specification provides for two USB High Speed Inter-Chip interfaces. The SoM-iMX6M does not support HSIC and hence all the pins for both interfaces are no connects.

### HSIC

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
272	HSIC_A_STRB	N/C	N/C	USB High Speed Inter-chip A Strobe
274	HSIC_A_DATA	N/C	N/C	USB High Speed Inter-chip A Data
275	HSIC_B_STRB	N/C	N/C	USB High Speed Inter-chip B Strobe

<b>277</b>	HSIC_B_DATA	N/C	N/C	USB High Speed Inter-chip B Data
------------	-------------	-----	-----	----------------------------------

**2.4.7 SPI**

The SoM-iMX6M provides two Serial Peripheral Interface busses each with three slave select lines. While three slave selects are provided for each SPI interface, any processor GPIO pin may be used as a slave select line. The serial NOR flash is connected to the ECSPi3 bus and uses ECSPi3\_SS0.

**Serial Peripheral Interface A**

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>222</b>	SPI_A_MOSI	ECSPi1_MOSI	GPIO5_IO23	Serial Peripheral Interface A, Master Out Slave In
<b>224</b>	SPI_A_MISO	ECSPi1_MISO	GPIO5_IO24	Serial Peripheral Interface A, Master In Slave Out
<b>226</b>	SPI_A_CLK	ECSPi1_SCLK	GPIO5_IO22	Serial Peripheral Interface A, Serial Clock
<b>228</b>	SPI_A_CS0#	ECSPi1_SS1	GPIO5_IO09	Serial Peripheral Interface A, Chip Select 0
<b>230</b>	SPI_A_CS1#	ECSPi1_SS2	GPIO4_IO11	Serial Peripheral Interface A, Chip Select 1
<b>114</b>	SPI_A_CS2#	GPIO16	GPIO7_IO11	Serial Peripheral Interface A, Chip Select 2

**Serial Peripheral Interface B**

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>219</b>	SPI_B_MOSI	ECSPi3_MOSI	GPIO4_IO22	Serial Peripheral Interface B, Master Out Slave In
<b>221</b>	SPI_B_MISO	ECSPi3_MISO	GPIO4_IO23	Serial Peripheral Interface B, Master In Slave Out
<b>223</b>	SPI_B_CLK	ECSPi3_SCLK	GPIO4_IO21	Serial Peripheral Interface B, Serial Clock
<b>225</b>	SPI_B_CS0#	ECSPi3_SS0	GPIO4_IO24	Serial Peripheral Interface B, Chip Select 0
<b>227</b>	SPI_B_CS1#	ECSPi3_SS1	GPIO4_IO25	Serial Peripheral Interface B, Chip Select 1
<b>280</b>	SPI_B_CS2#	ECSPi3_SS3	GPIO4_IO27	Serial Peripheral Interface B, Chip Select 2

### 2.4.8 MCI Multimedia Card

The SoM-iMX6M provides two SDIO/MMC interfaces for media cards or external peripheral interfacing. Both interfaces provide support for 4-bit mode. The EM4C Specification has the provision for a single 8-bit SDIO/MMC port however the SoM-iMX6M implements the dual 4-bit version.

#### MMC/SD Card Interface A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
203	MMC_A_CD	SD2_CD_B	GPIO1_IO4	SDIO/MMC A Card Detect
205	MMC_A_CMD	SD2_CMD	GPIO1_IO11	SDIO/MMC A Command
206	MMC_A_CLK	SD2_CLK	GPIO1_IO10	SDIO/MMC A Clock
212	MMC_A_DAT0	SD2_DATA0	GPIO1_IO15	SDIO/MMC A Data 0
209	MMC_A_DAT1	SD2_DATA1	GPIO1_IO14	SDIO/MMC A Data 1
214	MMC_A_DAT2	SD2_DATA2	GPIO1_IO13	SDIO/MMC A Data 2
211	MMC_A_DAT3	SD2_DATA3	GPIO1_IO12	SDIO/MMC A Data 3

#### MMC/SD Card Interface B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
207	MMC_B_CD	SD4_VSELECT	GPIO6_IO14	SDIO/MMC B Card Detect
210	MMC_B_CMD	SD4_CMD	GPIO7_IO09	SDIO/MMC B Command
208	MMC_B_CLK	SD4_CLK	GPIO7_IO10	SDIO/MMC B Clock
216	MMC_B_DAT0	SD4_DATA0	GPIO2_IO08	SDIO/MMC B Data 0
213	MMC_B_DAT1	SD4_DATA1	GPIO2_IO09	SDIO/MMC B Data 1
218	MMC_B_DAT2	SD4_DATA2	GPIO2_IO10	SDIO/MMC B Data 2
215	MMC_B_DAT3	SD4_DATA3	GPIO2_IO11	SDIO/MMC B Data 3

### 2.4.9 Serial Ports

The SoM-iMX6M provides four serial ports, three with RTS and CTS handshaking and one with full handshaking. All serial ports are TTL level and will require either an RS232 or RS485 driver/receiver for interfacing to external devices. Serial port A is generally used as the SoM debug port however this can be changed with custom software.

#### Serial Port A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
243	UART_A_TXD	UART2_TX_DATA	GPIO3_IO26	TTL Level Serial Port A Transmit Data
245	UART_A_RXD	UART2_RX_DATA	GPIO3_IO27	TTL Level Serial Port A Receive Data
247	UART_A_RTS	UART2_RTS_B	GPIO3_IO29	TTL Level Serial Port A Request To Send
241	UART_A_CTS	UART2_CTS_B	GPIO3_IO28	TTL Level Serial Port A Clear To Send

#### Serial Port B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
236	UART_B_TXD	UART1_TX_DATA	GPIO5_IO28	TTL Level Serial Port B Transmit Data
238	UART_B_RXD	UART1_RX_DATA	GPIO5_IO29	TTL Level Serial Port B Receive Data
234	UART_B_CTS	UART1_CTS_B	GPIO3_IO19	TTL Level Serial Port B Clear To Send
240	UART_B_RTS	UART1_RTS_B	GPIO3_IO20	TTL Level Serial Port B Request To Send
242	UART_B_DCD	UART1_DCD_B	GPIO3_IO23	TTL Level Serial Port B Data Carrier Detect
244	UART_B_DSR	UART1_DSR_B	GPIO3_IO25	TTL Level Serial Port B Data Set Ready
246	UART_B_DTR	UART1_DTR_B	GPIO2_IO24	TTL Level Serial Port B Data Terminal Ready
248	UART_B_RI	UART1_RI_B	GPIO2_IO31	TTL Level Serial Port B Ring Indicator

#### Serial Port C

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
-------------	--------------	-----------------------	-----------	-------------



<b>140</b>	UART_C_TXD	UART4_TX_DATA	GPIO5_IO30	TTL Level Serial Port C Transmit Data
<b>142</b>	UART_C_RXD	UART4_RX_DATA	GPIO5_IO31	TTL Level Serial Port C Receive Data
<b>144</b>	UART_C_RTS	UART4_RTS_B	GPIO6_IO02	TTL Level Serial Port C Request To Send
<b>146</b>	UART_C_CTS	UART4_CTS_B	GPIO6_IO03	TTL Level Serial Port C Clear To Send

### Serial Port D

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>150</b>	UART_D_TXD	UART5_TX_DATA	GPIO6_IO00	TTL Level Serial Port D Transmit Data
<b>152</b>	UART_D_RXD	UART5_RX_DATA	GPIO6_IO01	TTL Level Serial Port D Receive Data
<b>156</b>	UART_D_RTS	UART5_RTS_B	GPIO6_IO04	TTL Level Serial Port D Request To Send
<b>158</b>	UART_D_CTS	UART5_CTS_B	GPIO6_IO05	TTL Level Serial Port D Clear To Send

#### 2.4.10 I2S

The SoM-iMX6M provides dual I2S audio interfaces for connecting to an audio codec or other peripheral hardware. The I2S audio master clock is derived from a 12.288MHz oscillator on the SoM. The oscillator can be disabled by writing port GPIO6\_IO07 low.

### I2S A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>187</b>	I2S_A_RXD	AUD4_RXD	GPIO5_IO17	Integrated Inter-chip Sound A Serial Receive
<b>189</b>	I2S_A_TXFS	UAD4_TXFS	GPIO5_IO16	Integrated Inter-chip Sound A Frame Sync
<b>191</b>	I2S_A_TXD	AUD4_TXD	GPIO5_IO15	Integrated Inter-chip Sound A Serial Transmit
<b>193</b>	I2S_A_TXC	AUD4_TXC	GPIO5_IO14	Integrated Inter-chip Sound A Serial Clock
<b>195</b>	I2S_A_CLK	12.288MHz Oscillator Output	Not Driven by i.MX6	Integrated Inter-chip Sound A Master Clock

## I2S B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
186	I2S_B_RXD	AUD6_RXD	GPIO4_IO20	Integrated Inter-chip Sound B Serial Receive
188	I2S_B_TXFS	AUD6_TXFS	GPIO4_IO19	Integrated Inter-chip Sound B Frame Sync
190	I2S_B_TXD	AUD6_TXD	GPIO4_IO18	Integrated Inter-chip Sound B Serial Transmit
192	I2S_B_TXC	AUD6_TXC	GPIO4_IO17	Integrated Inter-chip Sound B Serial Clock
194	I2S_B_CLK	12.288MHz Oscillator Output	Not Driven by i.MX6	Integrated Inter-chip Sound B Master Clock

## 2.4.11 CAN

The SoM-iMX6M has two CAN interfaces. Both interfaces provide RX and TX lines. A CAN transceiver (ex. SN65HVD232) will need to be provided on the carrier board as well as signal termination.

## CAN A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
200	CAN_A_TX	FLEXCAN1_TX	GPIO1_IO07	Controller Area Network A Transmit Data
202	CAN_A_RX	FLEXCAN1_RX	GPIO1_IO08	Controller Area Network A Receive Data

## CAN B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
197	CAN_B_TX	FLEXCAN2_TX	GPIO4_IO14	Controller Area Network B Transmit Data
199	CAN_B_RX	FLEXCAN2_RX	GPIO4_IO15	Controller Area Network B Receive Data

## 2.4.12 GPIO

This section provides for the SoM-iMX6M’s general purpose IO section. All of these pins can be configured to be general-purpose digital ports and a 3.3V compatible. They can also be configured to take advantage of several of the functions of the SoM-iMX6M’s internal silicon. There are 22 total GPIO pins 4 of which are connected to the i.MX6’s PWM controller and two connect to the general purpose timer. GPIO15 also serves as an SPDIF input channel.

### PWM

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
2	GPIO0/PWMA	GPIO4_IO29/PWM1_OUT	General Purpose Input/Output PWM Output A
4	GPIO1/PWMB	GPIO4_IO30/PWM2_OUT	General Purpose Input/Output PWM Output B
8	GPIO2/PWMC	GPIO1_IO17/PWM3_OUT	General Purpose Input/Output PWM Output C
10	GPIO3/PWMD	GPIO1_IO18/PWM4_OUT	General Purpose Input/Output PWM Output D

### Timers/Counters

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
14	GPIO4/TCA	GPIO1_IO16/GPT_CAPTURE1	General Purpose Input/Output Timer Counter A
16	GPIO5/TCB	GPIO1_IO20/GPT_CLKIN	General Purpose Input/Output Timer Counter B

### General Purpose IO

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
20	GPIO6	GPIO5_IO05	General Purpose Input/Output
22	GPIO7	GPIO5_IO06	General Purpose Input/Output
26	GPIO8	GPIO5_IO07	General Purpose Input/Output
28	GPIO9	GPIO5_IO08	General Purpose Input/Output

<b>32</b>	GPIO10	GPIO5_IO10	General Purpose Input/Output
<b>34</b>	GPIO11	GPIO5_IO18	General Purpose Input/Output
<b>255</b>	GPIO12	GPIO5_IO19	General Purpose Input/Output
<b>256</b>	GPIO13	GPIO5_IO20	General Purpose Input/Output
<b>257</b>	GPIO14	GPIO5_IO21	General Purpose Input/Output
<b>258</b>	GPIO15	GPIO3_IO21/SPDIF_IN	General Purpose Input/Output
<b>259</b>	GPIO16	GPIO4_IO09	General Purpose Input/Output
<b>260</b>	GPIO17	GPIO4_IO28/ECSPI3_RDY	General Purpose Input/Output
<b>261</b>	GPIO18	GPIO2_IO23	General Purpose Input/Output
<b>262</b>	GPIO19	GPIO2_IO24	General Purpose Input/Output
<b>263</b>	GPIO20	GPIO2_IO25	General Purpose Input/Output
<b>264</b>	GPIO21	GPIO1_IO06	General Purpose Input/Output

### 2.4.13 LVDS

The SoM-iMX6M provides a 24-bit LVDS interface for video display. The LVDS interface supports 165 Mpixels/sec and provides I2C communication to the display.

#### LVDS

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>E3_9</b>	LVDS_D0-	LVDS0_DATA0_N	N/A	LVDS Data Pair 0-
<b>E3_10</b>	LVDS_D0+	LVDS0_DATA0_P	N/A	LVDS Data Pair 0+
<b>3</b>	LVDS_D1-	LVDS0_DATA1_N	N/A	LVDS Data Pair 1-
<b>5</b>	LVDS_D1+	LVDS0_DATA1_P	N/A	LVDS Data Pair 1+
<b>9</b>	LVDS_D2-	LVDS0_DATA2_N	N/A	LVDS Data Pair 2-
<b>11</b>	LVDS_D2+	LVDS0_DATA2_P	N/A	LVDS Data Pair 2+
<b>15</b>	LVDS_D3-	LVDS0_DATA3_N	N/A	LVDS Data Pair 3-

<b>17</b>	LVDS_D3+	LVDS0_DATA3_P	N/A	LVDS Data Pair 3+
<b>21</b>	LVDS_CLK-	LVDS0_CLK_N	N/A	LVDS Clock Pair -
<b>23</b>	LVDS_CLK+	LVDS0_CLK_P	N/A	LVDS Clock Pair +
<b>27</b>	LVDS_BL_CTRL	NAND_CS2_B	GPIO6_IO15	LVDS Backlight Control
<b>29</b>	LVDS_EN	NAND_CS3_B	GPIO6_IO16	LVDS Display Enable
<b>31</b>	LVDS_VDD_EN	EIM_BCLK	GPIO6_IO31	LVDS Power Enable
<b>37</b>	LVDS_I2C_SDA	TBD		LVDS I2C Serial Data
<b>39</b>	LVDS_I2C_SCL	TBD		LVDS I2C Serial Clock

#### 2.4.14 HDMI

The SoM-iMX6M provides one HDMI Version 1.4 port that is capable of up to 264MHz pixel clock. The HDMI port supports HDMI 1.4a, HDMI CTS 1.4a, DVI 1.0 and HDCP 1.4 and Supports video resolution up to 1080p @ 120Hz.

#### HDMI

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>43</b>	HDMI_CLK+	HDMI_TX_CLK_P	N/A	HDMI Clock Pair +
<b>45</b>	HDMI_CLK-	HDMI_TX_CLK_N	N/A	HDMI Clock Pair -
<b>49</b>	HDMI_D0+	HDMI_TX_DATA0_P	N/A	HDMI Data Pair 0+
<b>51</b>	HDMI_D0-	HDMI_TX_DATA0_N	N/A	HDMI Data Pair 0-
<b>55</b>	HDMI_D1+	HDMI_TX_DATA1_P	N/A	HDMI Data Pair 1+
<b>57</b>	HDMI_D1-	HDMI_TX_DATA1_N	N/A	HDMI Data Pair 1-
<b>61</b>	HDMI_D2+	HDMI_TX_DATA2_P	N/A	HDMI Data Pair 2+
<b>63</b>	HDMI_D2-	HDMI_TX_DATA2_N	N/A	HDMI Data Pair 2-
<b>67</b>	HDMI_HPD	HDMI_TX_HPD	N/A	HDMI Hot Plug Detect
<b>69</b>	HDMI_CAD	NAND_WP_B	GPIO6_IO09	HDMI Cable Detect

<b>71</b>	HDMI_CEC	HDMI_TX_CEC_LINE	GPIO5_IO02	HDMI CEC Communication
<b>73</b>	HDMI_I2C_SCL	TBD		HDMI DDC/I2C Serial Clock
<b>75</b>	HDMI_I2C_SDA	TBD		HDMI DDC/I2C Serial Data

**2.4.15 CSI**

The SoM-iMX6M has CSI (camera serial interface) that supports up to 1Gbps per data lane. There are four total lanes included on the SoM.

**CSI**

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>160</b>	CSI_CLK-	CSI_CLK0_N	N/A	Camera Serial Interface Clock Pair -
<b>162</b>	CSI_CLK+	CSI_CLK0_P	N/A	Camera Serial Interface Clock Pair +
<b>164</b>	CSI_DAT0-	CSI_DATA0_N	N/A	Camera Serial Interface Data Pair 0-
<b>168</b>	CSI_DAT0+	CSI_DATA0_P	N/A	Camera Serial Interface Data Pair 0+
<b>170</b>	CSI_DAT1-	CSI_DATA1_N	N/A	Camera Serial Interface Data Pair 1-
<b>172</b>	CSI_DAT1+	CSI_DATA1_P	N/A	Camera Serial Interface Data Pair 1+
<b>174</b>	CSI_DAT2-	CSI_DATA2_N	N/A	Camera Serial Interface Data Pair 2-
<b>176</b>	CSI_DAT2+	CSI_DATA2_P	N/A	Camera Serial Interface Data Pair 2+
<b>178</b>	CSI_DAT3-	CSI_DATA3_N	N/A	Camera Serial Interface Data Pair 3-
<b>180</b>	CSI_DAT3+	CSI_DATA3_P	N/A	Camera Serial Interface Data Pair 3+

**2.4.16 DSI**

The SoM-iMX6M includes a DSI (display serial interface) with two lanes that support up to 1GHz each. The DSI interface supports the MIPI DSI standard as well as DSI Version 1.01, DPI Version 2.0, DBI Version 2.0 and DCS Version 1.02.

**DSI**

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
-------------	--------------	-----------------------	-----------	-------------

<b>267</b>	DSI_CLK+	DSI_CLK0_P	N/A	Display Serial Interface Clock Pair +
<b>269</b>	DSI_CLK-	DSI_CLK0_N	N/A	Display Serial Interface Clock Pair -
<b>268</b>	DSI_D0+	DSI_DATA0_P	N/A	Display Serial Interface Data Pair 0+
<b>270</b>	DSI_D0-	DSI_DATA0_N	N/A	Display Serial Interface Data Pair 0-
<b>271</b>	DSI_D1+	DSI_DATA0_P	N/A	Display Serial Interface Data Pair 1+
<b>273</b>	DSI_D1-	DSI_DATA0_N	N/A	Display Serial Interface Data Pair 1-

### 2.4.17 PCIe

The SoM-iMX6M includes one PCIe interface. The EM4C SoM Specification includes two lanes however the i.MX6 processor only provides one lane. The interface supports PCIe v2.0. PCIe B is not implemented on the SoM-iMX6M and all pins are no connect.

#### PCIe A

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>85</b>	PCIE_A_CLK+	CLK1_P	N/A	PCIe A Clock Pair +
<b>87</b>	PCIE_A_CLK-	CLK1_N	N/A	PCIe A Clock Pair -
<b>91</b>	PCIE_A_TX+	PCIE_TX_P	N/A	PCIe A Transmit Data +
<b>93</b>	PCIE_A_TX-	PCIE_TX_N	N/A	PCIe A Transmit Data -
<b>97</b>	PCIE_A_RX+	PCIE_RX_P	N/A	PCIe A Receive Data +
<b>99</b>	PCIE_A_RX-	PCIE_RX_N	N/A	PCIe A Receive Data -
<b>113</b>	PCIE_A_CLK_OE	GPIO2_IO00	N/A	PCIe A Clock Output Enable

#### PCIe B

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>79</b>	PCIE_B_CLK+	N/C	N/C	PCIe B Clock Pair CLK+
<b>81</b>	PCIE_B_CLK-	N/C	N/C	PCIe B Clock Pair CLK-
<b>103</b>	PCIE_B_TX+	N/C	N/C	PCIe B Transmit Data +

<b>105</b>	PCIE_B_TX-	N/C	N/C	PCIe B Transmit Data -
<b>109</b>	PCIE_B_RX+	N/C	N/C	PCIe B Receive Data +
<b>111</b>	PCIE_B_RX-	N/C	N/C	PCIe B Receive Data -
<b>115</b>	PCIE_B_CLK_OE	N/C	N/C	PCIe B Clock Output Enable

### PCIe Control

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>119</b>	PCIE_RST#	POR#	N/A	PCIe Reset (active low)
<b>107</b>	PCIE_PRESEN#	GPIO2_IO01	N/A	PCIe Presence (active low)
<b>117</b>	PCIE_WAKE#	GPIO2_IO02	N/A	PCIe Wake

### 2.4.18 SATA

The SoM-iMX6M provides a SATA II interface that supports 3.0Gbps.

### SATA

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
<b>123</b>	SATA_RX+	SATA_PHY_RX_P	N/A	Serial ATA Receive Data Pair +
<b>125</b>	SATA_RX-	SATA_PHY_RX_N	N/A	Serial ATA Receive Data Pair -
<b>135</b>	SATA_TX+	SATA_PHY_TX_P	N/A	Serial ATA Transmit Data Pair +
<b>137</b>	SATA_TX-	SATA_PHY_TX_N	N/A	Serial ATA Transmit Data Pair -
<b>133</b>	SATA_ACT#	GPIO6_IO10	N/A	Serial ATA Activity (active low)

### 2.4.19 Battery Control

The battery control section for the SoM-iMX6M is for controlling external battery charging circuitry for a SoM based tablet or similar hardware.

### Battery Control



SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Port Line	Description
86	BATLOW#	NAND_DATA03	GPIO2_IO03	Battery Low Indicator (active low)
90	I2C_PM_DAT	N/C	N/C	PMIC I2C Serial Data
92	I2C_PM_CLK	N/C	N/C	PMIC I2C Serial Clock
96	CHARGE#	NAND_DATA04	GPIO2_IO04	Battery Full Indicator (active low)
98	CHARGE_DET#	NAND_DATA05	GPIO2_IO05	Battery Charging Indicator (active low)
102	TEST#	NAND_DATA06	GPIO2_IO06	
104	SLEEP#	NAND_DATA07	GPIO2_IO07	

**2.4.20 Analog to Digital Converter**

The SoM-iMX6M has an onboard four channel 12-bit analog to digital converter. The SoM uses a Microchip MCP3204 A/D converter. The A/D converter is interfaced through ECSPi1 bus and is connected to ECSPi1\_SS0. The A/D converter is capable of 50Ksps with 2.7V supply and 100Ksps with 5V supply. The MCP3204 is powered by 3.3V so a sample rate of over 50Ksps is guaranteed. An external ADC voltage reference can be supplied to the SoM through SoM Pin# 35 or an internal 3.3V reference can be selected in software.

**ADC**

SODIMM Pin#	SoM Pin Name	MCP3204 Pin Name(s)	Port Line	Description
86	ADC_1	CH0	N/A	Analog to Digital Converter Channel 1
90	ADC_2	CH1	N/A	Analog to Digital Converter Channel 3
92	ADC_3	CH2	N/A	Analog to Digital Converter Channel 4
96	ADC_4	CH3	N/A	Analog to Digital Converter Channel 5
35	ADC_VREF	External ADC Reference	N/A	External ADC Reference Voltage, 3.3V Max

**2.4.21 Touch Screen Interface**

A resistive touch screen interface is provided on the SoM-iMX6M by use of a TSC2005 touch screen controller. The TSC2005 is connected to the i.MX6 processor through ECSPi1 and uses ECSPi1\_SS1.

## Touch Screen Interface

SODIMM Pin#	SoM Pin Name	TSC2005 Pin Name(s)	Port Line	Description
36	TOUCH_X+	X+	N/A	Resistive Touch X+ Sense
38	TOUCH_X-	X-	N/A	Resistive Touch X- Sense
40	TOUCH_Y+	Y+	N/A	Resistive Touch Y+ Sense
44	TOUCH_Y-	Y-	N/A	Resistive Touch Y- Sense

## 2.5 Power Connections

The SoM-iMX6M can be powered from a single 5V supply.

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
E1_1, E2_1	5V_VSB	N/A	5 Volt Standby Supply
E1_2, E2_2, E1_3, E2_3, E1_4, E2_4, E1_5, E2_5, E1_6, E2_6, E1_7, E2_7, E1_8, E2_8, E1_9, E2_9, E1_10, E2_10	5V_VCC	N/A	5 Volt Power Supply
266, 265, 250, 249, 239, 232, 229, 220, 217, 204, 201, 198, 185, 184, 177, 166, 154, 153, 148, 171, 147, 124, 121, 101, 100, 95, 94, 89, 88, 83, 77, 66, 65, 60, 59, 54, 53, 48, 47, 42,	GND	N/A	Ground

41, 30, 25, 24, 19, 18, 13, 12, 7, 6, 1, E4_10, E3_8, E4_7, E4_4, E4_1, E3_1			
--	--	--	--

**2.6 Boot Options**

The SoM-iMX6M provides four lines for boot selection. BOOT\_0 and BOOT\_1 are connected directly to the i.MX6 processor. BOOT\_2 and BOOT\_3 are connected to internal logic to allow for additional boot modes.

SODIMM Pin#	SoM Pin Name	Processor Pin Name(s)	Description
74	BOOT_0	BOOT_MODE0	Processor Boot Options Select 0
76	BOOT_1	BOOT_MODE1	Processor Boot Options Select 1
276	BOOT_2	N/A	Additional Boot Options Select 2
278	BOOT_3	N/A	Additional Boot Options Select 3

Include table for different boot options.

**2.7 Serial Data Flash**

The SoM-iMX6M has a 16MB serial NOR flash that can be used to boot the SoM. The Serial Data Flash is connected to SPI3 and uses SPI3\_SS0 to enable it. The Serial Data Flash also has a Write Protect Provision. To Write Protect the Serial Data Flash pull SoM pin# 279 low. This pin is pulled up by a 10K ohm resistor on the module so if write protect is not desired the SoM pin can simply be left floating.

If this feature is required it would be implemented on the carrier as a jumper or an I/O line.

**2.8 Module Status LED**

A green status LED (LD1) is active-high and is controlled by port line GPIO1\_IO26.

**3 Design Considerations**

One of the goals of the SoM-iMX6M is to provide a modular, flexible and inexpensive solution capable of delivering high-end microcontroller performance.

### 3.1 Power

The SoM-iMX6M requires a voltage of 5.0V at ##00mA. For a bare-bones population, users can get away with using only 5.0V, and simply provide this to all the voltage inputs listed in Power Connections section. This however, will not provide battery backup for the RTC.

#### 3.1.1 Battery Backup

The SoM-iMX6M real-time clock (RTC) requires a backup voltage to maintain its data. This backup voltage comes from SoM Pin# 281, VCC\_RTC, and should be connected to 3.3 volts.

The RTC will draw approximately XXuA when the processor is not powered by the 5.0V supply. When the module is powered no current is drawn from the backup battery supply. If the RTC is not needed, this can be tied to 3.3V.

#### 3.1.2 Analog Reference

The SoM-iMX6M has both an external and internal ADC voltage reference. The internal voltage reference is 3.3V and can be disabled through software by writing GPIOxxxx High. The external ADC reference voltage can range from 0 to 3.3V. In order to use the onboard ADC reference the external.

## 4 Software

The SoM-iMX6M offers a wide variety of software support from both open source and proprietary sources. The hardware core was designed to be software compatible with the Freescale i.MX6 reference design, which is supported by Linux.

For more information on software support, please visit the EMAC Wiki Software Section at:

<http://wiki.emacinc.com/wiki/Software?prodNum=SoM-iMX6M>

## 5 Dimensions

